

# Z-ERA05

This chapter covers the following topics:

- Description
  - Parameters
  - Return Codes
  - Subprograms
  - Example
- 

## Description

Mark a cabinet for deletion.

This subprogram can be used only by a supervisor or cabinet administrator.

After a cabinet has been marked for deletion, it is not deleted until the Con-nect utility B04050 is run. See the *Con-nect Utilities* documentation, section *Delete Pending Cabinets*.

The cabinet which has been marked for deletion is not deleted by the utility before the date specified in the parameter Delete-date has been reached.

You can also use this subprogram to cancel a deletion mark. To do so, you must mark the parameter Reset-flag for the specified cabinet. The return code 92 indicates that the deletion mark has been canceled.

Successful termination of Z-ERA05 always results in an END TRANSACTION. You are not able to control transaction handling.

## Parameters

Parameter	Format	In	Out	Remarks
Return-code	N2		X	
Cabinet	A8	R		The cabinet ID of a supervisor or cabinet administrator.
Password	A8	R		The password of the above cabinet.
Cabinet-delete	A8	R		The name of the cabinet to be deleted.
Delete-date	A8	O		Format yyyymmdd. The date specified is interpreted as GMT date with GMT time as 0. If a date is not specified, the current date is assumed.
Reset-flag	A1	O		If marked, the Cabinet-delete mark is canceled.

## Return Codes

00	Success
02	Invalid cabinet name
03	Password incorrect
15	Invalid administrator status
90	Cabinet record does not exist
91	Cabinet is already marked for deletion
92	Deletion mark of cabinet is canceled (not an error)
93	Invalid date format
94	Passed date
95	Cabinet-delete mark cannot be canceled, because the cabinet was not marked for deletion
96	Cabinet-delete is already marked for rename

## Subprograms

Z-120

Z-122

Z-123

Z-1200&amp;0

## Example

```

0010 *
0020 * Example program to erase a cabinet
0030 *
0040 *
0050 DEFINE DATA
0060 LOCAL
0070 1 RETURN-CODE          (N2)
0080 1 CABINET              (A8)
0090 1 PASSWORD            (A8)
0100 1 CABINET-DELETE      (A8)
0110 1 DELETE-DATE         (A8)
0120 1 RESET-FLAG          (A1)
0130 *
0140 END-DEFINE
0150 *
0160 RESET RETURN-CODE
0170 MOVE 'ADMIN'          TO CABINET
0180 MOVE 'ADMIN'          TO PASSWORD
0190 MOVE 'FBL'            TO CABINET-DELETE
0200 MOVE '19931224'       TO DELETE-DATE
0210 *
0220 *
0230 CALLNAT 'Z-ERA05'
0240   RETURN-CODE
0250   CABINET
0260   PASSWORD

```

```
0270  CABINET-DELETE
0280  DELETE-DATE
0290  RESET-FLAG
0300  *
0310  IF RETURN-CODE EQ 0
0320      WRITE 'Cabinet was marked for deletion'
0330  ELSE
0340      WRITE 'Return code :' RETURN-CODE
0350  END-IF
0360  *
0370  END
```